

UP800V - Digital handsfree audio receiver with touch function icons and expandable with a video display



Easy conversion of the UP800V audio unit in the MP800 video monitor

Flat front, handsfree with touch and backlit function icons and expandable with video display. ACO receivers are solid devices, made of the highest quality materials, functional and easy to use. Minimalist form allows for versatile use of the devices in various types of investments.

Compatible with digital control panels and panels from groups: CDNP, Inspiro and Familio P/PV

Index	UP800V (G2)
Description	Active digital handsfree receiver with flat front with touch function icons for PV systems.
Material	ABS plastic housing
Dimensions (mm)	198,3x81,5x26,5
Mounting	Surface mounted
Available colours	White
Hanging up the handset	-
Display	None Optional - LCD display module: - UP800 LCD 3.5"
Type of installation	Digital PV system: twisted pair cat. 5e or 6 6
Power supply	15VDC / 280 mA
Standby power consumption	~0,2W
Outputs	The " Circle" button (Function button F2): - on the system bus - 2 x ARK screw connectors: NO contact: 2A/24VDC (potential-free, separated from the system) - after holding down the 3s buttons
Inputs	1 x RJ45 socket (bus connection) 4 x ARK screw connectors audio and power line connection 1 x screw connector "RING": - connection of NO contact e.g. "bell" button - doorbell function (activated after a contact with the system GND) 2 x ARK screw connectors connection of the video signal 1 x 10-pin connector connection of an optional 3,5" LCD display
Attributes	<ul style="list-style-type: none"> - illuminated tactile icons - hands-free - 7-stage adjustment of the sounds (ringing and call) - clear, interference-free sound - full privacy of the connection - intuitive and comfortable to use - possibility to work several receivers at one address - doorbell function (RING) - uniphone can receive any call address (after setting "0") - home automation: control of external devices, e.g. gate, barrier, roller shutters, lighting (some models of control panels or panels require an optional CDN-I/O relay module) - opening or controlling the home automation without answering the call - Built-in relay outputs activated independently for 1s (potential-free, separated from the system), - Auto open function (when the ringing is detected, the door will open) - optical indication of call silencing - call signalling - compatible with all digital devices from the CDNP, Inspiro and Familio P/PV groups <p>The possibility of changing the uniphone into a video monitor after installing a dedicated 3.5" UP800 LCD display, we gain:</p> <ul style="list-style-type: none"> - colorful, clear image - possibility to call up the image preview in the standby mode and the possibility to switch the preview on permanently - easy installation of the display (can be done by the end user)

KK0118envB.2029



ACO sp. z o.o. sp. komandytowa
ul. Diamentowa 7, 62-002 Suchy Las

T: +48 61 843 93 71
E: biuro@aco.com.pl

NIP: 9721258093
REGON: 362759523

www.aco.com.pl
www.support.aco.com.pl

