




- High sensitivity PIR sensor
- Brightness level and time delay can easily be adjusted via control knobs
- Circular detection area 360°
- Fitted for any lamp loads (LED, RLC, CFL)
- Zero-cross switching for relay-saving switching
- Functional test mode with red LED indicator
- Cover clips for limiting the detection range
- Connect several detectors in parallel to expand the detection area
- Optional IR remote control for easy and quick setting (lux, time, sensitivity threshold, manual override)

**Illuminate**

switching controlling counting


## Motion / presence detector 722 010 pir for ceiling mounting



### Technical data


<b>Supply voltage</b>	230 V, 50 Hz
<b>Power consumption</b> (real power)	< 1.0 W
<b>Channel</b> (potential of supply voltage)	Normally open
<b>Contact material</b>	AgSnO <sub>2</sub>
<b>Switching capacity</b>	16 A / 250 V~ at cosφ=1 9 A with inductive load cosφ=0,4
<b>Filament Lamp, Halogen Lamp</b>	3,000 W
<b>Fluorescent Lamp</b>	1,300 W (130 µF)
<b>LED Lamp</b>	1,300 W
<b>Energy Saving Lamp</b>	18x7 W, 12x11 W, 10x15 W, 10x20 W, 10x23 W
<b>Recommended installation height</b>	2.5 m
<b>Circular detection area</b>	360°, Ø 7 m
<b>Adjustable lux threshold</b>	3 - 100 lux
<b>Adjustable light switch-off delay</b>	6 sec. - 12 min.
<b>Permitted ambient temperature</b>	-10° ... +45°C
<b>Mounting</b>	Ceiling mounting
<b>Type of protection</b>	IP 40
<b>Class of protection</b>	II when installed according to regulations

### Single detector installation



### Accessories

IR remote control 700 000 pir



Order number	Switching contacts	Special function
paladin 722 010 pir	1	Zero-cross switching
Housing colour		