

**FAM-P** - Digital door entry system with key fob reader, direct call buttons and code lock.

Available versions: FAM-P-1NPACC, FAM-P-2NPACC, FAM-P-4NPACC, FAM-P-6NPACC, FAM-P-ZSACC, FAM-P-1ZSACC, FAM-P-2ZSACC.

All versions available in surface mounted version - index NT.



The door entry system is equipped with a proximity key fob reader, illuminated buttons and description fields.

Familio panels are dedicated for single and multi-family houses. The combination of modern technology with brushed stainless steel creates timeless solutions addressed to individual customers who appreciate design and functionality.

<b>Index</b>	FAM-P-1NPACC, FAM-P-2NPACC, FAM-P-4NPACC, FAM-P-6NPACC, FAM-P-ZSACC, FAM-P-1NPZSACC, FAM-P-2NPZSACC
<b>Description</b>	Digital door entry system with 1, 2, 4, 6 direct call buttons, illuminated description fields, proximity key fob reader and code lock.
<b>Material</b>	2mm thick flat front panel and illuminated brushed stainless steel buttons
<b>Modules</b>	xNP - 1, 2, 4 or 6 illuminated call buttons. ZS - Code lock for entering an individual four-digit opening code for each apartment or calling. ACC - 125 kHz Unique proximity key fob reader.
<b>Max. amount of phones</b>	Depending on the button version - 1, 2, 4 or 6 apartments or 10 in case of calling from a code lock.
<b>Mounting</b>	Flush-mounted Surface mounted NT
<b>Dimensions (mm)</b>	Flush-mounted panel 197x90 Flush-mounted mounting box 179x73x32 Surface mounted panel 174,8x67,8 Surface mounted box 177,1x70x36,5/25,4
<b>Installation type</b>	Digital: 2 wire
<b>Line length</b>	Max. 1000m
<b>Power supply</b>	11,5V AC lub 15V DC / 250mA
<b>Stand-by power consumption</b>	~ 1,3W
<b>Outputs</b>	To be connected: - traditional electric strik (max. 1A) or - a reversing door strike (max. 0.5A) or - CDN-PK relay module (max. 5A)
<b>Inputs</b>	1x NO e.g. "bell" button - direct activation of the electric door strike with the possibility of delay up to 255 seconds.
<b>Features for disabled</b>	- acoustic and optical signalling of panel functions - automatic or remote (push-button) door release without answering the call and the possibility of connecting an additional acoustic or light signalling device in the premises (CDN-U)
<b>Attributes</b>	- weatherproof and vandalism resistant - operation of up to 192 proximity tags - Support for multiple expansion modules to increase system functionality - Individually backlit call buttons with easily replaceable, backlit descriptive points - support for multi-part master/slave systems - Home automation: control of external devices, e.g. entrance gate, barrier, lighting, roller shutters (optional CDN-I/O or mini I/O module required) - possibility to connect multiple receivers under the same number (for active receivers) - wide range of possibilities for individual configuration of the settings for each unit - individual settings of sound parameters - intuitive and comfortable operation and configuration - corridor opening function - doorman's call - possibility of connecting different types of electric strikes - Electromagnetic jumper controllable (optional CDN-Pk module required) - operation of the external opening button - easily replaceable illuminated descriptive fields - compatible with all digital group devices: CDNP, Inspiro and Familio P/PV- Programming from a computer (optional CDN-USB module required) - free software available in the "download" tab

KK0141enVA.2002

