



2898



## DALI rotary potentiometer with power supply Soft-lock, Light control

### Technical features

### Functions

- for switching and controlling electr. ballasts and Tronic transformer with DALI/DSI interface

### Controls and indicators

- with soft-lock

### Main electrical features

Nominal voltage	230 V
Rated voltage	230 V AC

### Voltage

DALI voltage	16 V DC
--------------	---------

### Electric current

Output current	max. 52 mA
----------------	------------

### Fuse

- short-circuit and overload proof (electronic fuse)

### Power

Power consumption	≤ 2 W
-------------------	-------

### Dimensions

Axis dimension Ø	4 mm
------------------	------

### Connection

Quantity of DALI devices with an active DALI potentiometer	26
Quantity of DALI devices with 4 active DALI potentiometers in parallel	104
- with screw terminals	

### Cable

DALI cable length at 1.5 mm <sup>2</sup>	max. 200 m
--	------------

### Settings

- basic brightness programmable

### Scope of delivery

- with incremental encoder

### Equipment

---

- switch-on brightness level can be stored safe after power failure
  - e.g. for fluorescent lamps and LV halogen lamps
  - supplies the necessary control current for additional DALI users in the active operation to mains voltage
  - parallel connection of max. 4 active DALI potentiometers possible
  - without mains voltage in passive operation on DALI voltage the unit serves as an additional control
  - with on/off pressure switch
- 

### Use

---

- Soft-lock
- 

### Identification

---

Application, usage	Light control
Main design line	Light control

---

### Instructions

---

- Not suitable for combining with other DALI sensors or central units.
-