


KNX presence detector Mini Standard



Specification	Order No.	Packing unit	PS	EAN
	2220 00	1	06	4010337014683

Presence detector for presence monitoring (operating mode: presence detector), for motion detection (operating mode: ceiling sentinel) or for monitoring with alarm telegrams (operating mode: alarm device) indoors or outdoors. With their subtle and flat design and flexible installation concept, presence detectors Mini are particularly suitable for properties with high architectural demands.

Features

- Extreme flat installation.
- Terminal mounting on suspended ceilings.
- Ceiling mounting on stable ceilings in device box in accordance with DIN 49073 using optional accessories.
- Surface mounted installation in surface-mounted box (optional accessories).
- Protection type IP44 allows installation outdoors and in moistureprone areas.
- The colour emphasis of the design rings enables their colours to be adapted to the wall or ceiling.
- When the design ring has been removed, all the operating elements (e.g. the programming button) of the device can be conveniently accessed from the front. Thus, removal is not necessary for subsequent adjustment or programming via the ETS.
- Ceiling-mounted device with integrated KNX bus coupler.
- PIR sensors: three sensors, integrated brightness sensor.
- Sensitivity of the motion detection can be set manually using an adjuster.
- Sensitivity can be configured by ETS.
- Sensitivity adjuster on the device can be deactivated using the software.
- Indication of motion detection (permanent or only during walking test).
- One function block configurable.
- Adjustable operating mode: ceiling security-light, presence detector, alarm device.
- Individual device, main unit, auxiliary unit can be set.
- Operating mode for individual device or main unit: automatic, semi-automatic (manual ON / automatic OFF, or automatic ON / manual OFF).
- Two outputs (for function: ceiling security-light, presence detector).
- Output (for function: ceiling security-light, presence detector): switching, staircase function, switching with forced setting, dimming value transmitter, light scene auxiliary unit, temperature value transmitter, brightness value transmitter, temperature operating mode.
- Twilight stage can be set using external communication object or teach-in.
- Additional transmission delay via external communication object.
- Adaptive delay time (self-teaching additional transmission delay)
- Short-term presence function.

- Feedback of twilight stage.
 - Block function.
 - Manual actuation using pushbutton sensor (separate communication object).
 - Switch-off brightness (for presence detectors) via teach-in.
 - Measurement of time period after last motion.
-

Technical data

KNX medium:	TP256
Mounting height:	2.20 m to 5 m
Detection angle:	360°
Mounting height 3 m - Detection range:	Ø approx. 12 m
Brightness sensor - Measurement range: - Detection range:	10 to 2000 lx 5 m Ø
Profile height on ceiling - Design ring: - incl. lens:	1.25 mm 4.8 mm
Ambient temperature:	-25 °C to +55 °C
Relative humidity:	10 to 100% (without condensation)
Protection type:	IP44
Protection class:	III
KNX connection:	Connection and junction terminal
Installation depth:	34 mm

Notes

- The presence detector Mini is not suitable for alarm messages in VdS-compliant alarm systems.
-

Scope of supply

- Small design ring is included in the scope of supply.
 - KNX connection and junction terminal included in the scope of supply.
-

Dimensions in mm

Ceiling cut-out:	44	-
Dimensions (incl. small design ring):	53,5	38
